

LB800 Bootload Instructions

Version 1.0 - April, 2019

For Support: (310) 425-3425 ext. 122

What you will need:

PC or MAC, Cineo Fixture and USB 2.0+
Thumb Drive (for software loading)



Please Note: You must have firmware 1.04 installed
for these steps to work properly.

Steps:

1. Using a Mac or PC, download the firmware and save to your thumb drive. **Do not rename the file.**
2. Power on the LB800 and select Local Mode from the main menu.
3. Once in Local Mode, insert the USB thumb drive into the port on the back of the console. After a few moments the display will show "Wait 5 seconds and remove the USB".
4. After 5 seconds remove the USB thumb drive and immediately power the LB800 down.
5. At the top right, click "Browse", and locate the correct ".boot" file.
6. Next, turn the LB800 back on and wait for it to boot up completely. During this power on step, the current firmware revision will be shown on the display.
7. Lastly, go to the settings menu to perform a Factory Reset followed by another power cycle.
- 8..The LB800 should be up to date.

For additional questions and guidance on the LB800 operation, please see the User Guide for step by step instruction.