



DMX Personalities: LB800 with C²OS

MARCH 2021

PERSONALITY	DESCRIPTION	SLOT COUNT
1	1-Zone 8-bit HSIK	4
2	1-Zone 16-bit HSIK	8
3	1-Zone 8-bit RGBK	4
4	1-Zone 16-bit RGBK	8
5	1-Zone 8-bit HSIK-G	5
6	1-Zone 16-bit HSIK-G	10
7	1-Zone 8-bit RGBK-G	5
8	1-Zone 16-bit RGBK-G	10
9	10-Zone 8-bit HSIK	41
10	10-Zone 16-bit HSIK	82
11	10-Zone 8-bit RGBK	41
12	10-Zone 16-bit RGBK	82
13	10-Zone 8-bit HSIK-G	42
14	10-Zone 16-bit HSIK-G	84
15	10-Zone 8-bit RGBK-G	42
16	10-Zone 16-bit RGBK-G	84
17	2-Zone 8-bit HSIK	8
18	2-Zone 16-bit HSIK	16
19	2-Zone 8-bit RGBK	8
20	2-Zone 16-bit RGBK	16
21	2-Zone 8-bit HSIK-G	10
22	2-Zone 16-bit HSIK-G	20
23	2-Zone 8-bit RGBK-G	10
24	2-Zone 16-bit RGBK-G	20
25	1-Zone 8-bit DIM-Only	1
26	1-Zone 16-bit DIM-Only	2
27	1-Zone 8-bit DIM + CCT	2
28	1-Zone 16-bit DIM + CCT	4
29	2-Zone 8-bit DIM-Only	2
30	2-Zone 16-bit DIM-Only	4
31	2-Zone 8-bit DIM + CCT	4
32	2-Zone 16-bit DIM + CCT	8
33	Local Control	-